



Nothing else measures up!

Follow us!



Prospect House
George Cayley Drive
Clifton Moor
York
England
YO30 4XE

Tel: +44 (0) 1904 692723
Fax: +44 (0) 1904 690385

E-Mail: sales@yorksurvey.co.uk



Elite LED Rechargeable Slimline Torch



Code: 53221

Operating Instructions

Elite LED Rechargeable Slimline Torch

This versatile pocket inspection torch utilises the latest technology in portable lighting, allowing an extremely bright light to be encased in a lightweight and slimline compact unit.

The powerful 200 lumen COB LED features three light settings:

- White light - solid dimmable
- @ed light - solid
- Red light - solid

A strong magnet in the base enables the torch to be fixed to metalwork. The cleverly designed pocket clip allows for the torch to be attached to clothing or a belt. A recess on the rear enables fixing to a substrate via a screw.

An ideal companion for use in all trades and around the home or car. The compact design makes it an ideal leisure torch offering minimal storage space and weight.

Specifications

| | |
|-------------------------|-------------------------------|
| Brightness | 200 lumens |
| Beam distance | 30 metres |
| Run time | 1.5 hours |
| Light source | COB LED |
| Battery | 3.7V Polymer Li-ion 500mAh |
| Charge time | approx 2 hours |
| Impact resistant | 1 metre |
| Water resistant | IP64 |
| Weight | 37g |
| Dimensions | 123 x 25 x 12mm |
| Supplied with | USB Charging Lead |

Battery Recharging

The torch must be fully charged for a minimum of 2 hours before being used for the first time, this will ensure that the battery gives its best performance now and on future recharging cycles.

The charging cable is for recharging the battery only. It cannot be used to directly power the light.

Failure to recharge the light every 3 months may permanently damage or reduce the performance of the light.

The battery charge does not have to be fully depleted before recharging.

Using the Charging Lead

Plug the USB charger lead into the micro USB charging socket on the side of the torch. Plug the other end of the lead into any USB charging outlet

While on charge the small charging indicator lamp will glow red and will turn blue when the battery is fully charged (approximately 2 hours).

Please note the following

1) For the best performance Li-Ion batteries should not be stored for prolonged periods without being charged at regular intervals.

2) Manufacturers recommend keeping the battery in a state-of-charge of 40 - 50% when placing in storage. If in doubt, keep the light in a higher charged state in a cool place.

3) Self-discharge rate is approximately 10% per month.

Operating Instructions

The inspection light output functions are controlled by a sequential switch on the front of the light.

- Press and release the button to turn on the white light.
- Press and release the button again to turn on the red light.
- Press and release button again to change to flashing red light.

- Alternatively, press and hold the button for two seconds to turn on red light, skipping the white light stage.

The white light has a dimmable function:

- With the white light turned on, press and hold the button down to increase or decrease brightness. The light will flash to indicate when it has reached the highest or lowest level. Release the button when the desired light output is reached.

Under optimum conditions, with a full charge, the light can normally be used for 1.5 hours.

To achieve the best performance from your LED Mini Slimline Torch, always switch the light off when the battery power begins to run low, and recharge immediately.

Cleaning

Clean the light using a soft cloth, dampened with a soap and water solution.

Do not immerse or submerge the light in water or any other fluid.

Maintenance

There are no serviceable parts inside this light. Opening or visible attempts to repair the light will void any guarantee.

LED bulbs should not wear out under normal conditions and do not need to be replaced.



Never attempt to open a battery, as liquid may be ejected, if accidental contact occurs flush the affected area with water. If the liquid comes into contact with the eyes flush with water and seek medical help. Liquid ejected from batteries may cause irritation or burns.



Li-ion batteries are formulated from environmentally sensitive materials and must be disposed of properly.

Please return these batteries to your local recycling centre where they will be

recycled or disposed of properly.



Never attempt to incinerate batteries as they may leak or explode.

One-Year Home Use Limited Guarantee

Lighthouse guarantees this product to the original purchaser for a period of ONE YEAR against any defects in material or workmanship but shall not cover damage caused by misuse, abuse, alteration or accident. This product is intended for home use only and the guarantee will not cover products used for commercial purposes.